

**13W CFL Drop Light w/ Inline Transformer - 825 Lumens - 120-277V AC to 12V DC -Dual Hooks - 50' Cord**

Part #: [FTL-2-CFL-X12V-50](#)



The FTL-2-CFL-X12V-50 from Larson Electronics is a compact fluorescent drop light that is designed for heavy-duty applications in industrial facilities. This luminary emits 825 lumens of white light for robust illumination. An attached inline transformer steps down 120-277V AC to 12V DC for low voltage requirements. Padded end caps offer impact resistance, while dual hooks expand hands-free mounting options for operators in the work site.

The FTL-2-CFL-X12V-50 is a compact drop light that is suitable for handheld illumination in industrial facilities. This 13-watt unit provides 825 lumens of white light with a 5,000K color temperature rating. An inline AC to DC transformer steps 120-277V AC down to 12V DC for low voltage operation. Featuring a lifespan of 10,000+ hours, the fluorescent drop light is capable of illumination in environments ranging between 10°C and 45°C.

Constructed of polycarbonate, the luminary comes with an impact resistant build for extended reliability. The end caps are padded to absorb rough handling, vibrations and shock. Operators may use dual mounting hooks to quickly secure the unit on pipes, poles, corners, bases, chains and other compatible surfaces for hands-off operation.

[Click Photos to Enlarge](#)



**5-15 Straight Blade Plug**  
15 Amp / 125V Rated



**L5-15 Twist Lock Plug**  
15 Amp / 125V Rated



**L6-15 Twist Lock Plug**  
15 Amp / 250V Rated



**UK BS1363 Straight Blade Plug**  
13 Amp / 250V Rated / Internal Fuse



**Intl Schuko 2-Pin Plug**  
16 Amp / 250V Rated / Grounded



**Flying Leads / Pigtail Wires**

**Wiring/Power:** This CFL drop light is equipped with 50' of 18/2 SJTOW cord that is fitted with an industrial grade cord cap for easy connection to common wall outlets. Plug options include standard 5-15 15 amp straight blade plug for 110V wall outlets with ground, standard 6-15 15 amp straight blade plug for 220-240V wall outlets with ground, NEMA L5-15 15 amp twist lock plug for 125V twist lock outlets, NEMA L6-15 15 amp twist lock plug for 240V twist lock outlets, British BS1363 13 amp fused 3-blade plug for United Kingdom outlets, or a two pin 16 amp rated Schuko plug with ground contact and socket for European outlets up to 250V. Alternatively, we can provide flying leads with no plug for hard wire

applications or for operators who prefer to wire in user provided cord caps. Please choose pigtail option below for flying leads with no plug.

**Applications:** Inspections, task lighting, detailed work, industrial facilities, handheld lighting, monitoring, general illumination, low voltage lighting and more.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message sales@larsonelectronics.com for more information about our custom options tailored to meet your specific industry needs.

#### **Specifications / Additional Information**

##### **FTL-2-CFL-X12V-50 CFL Drop Light**

**Lamp Type:** Compact Fluorescent Light

**Dimensions:** 5" x 15" x 5"

**Weight:** 7 lbs

**Input Voltage:** 120-277V AC

**Output Voltage:** 12V DC

**Total Watts:** 13 Wats

**Lumens:** 825 Lumens

**CFL Life Expectancy:** 10,000+ hours

**Light Color:** White

**Correlated Color Temperature:** 5000K

**Ambient Operating Temp Range:** 10°C to +45°C

**Housing Material:** Polycarbonate

**Mount:** Dual Hooks

**Cord:** 50' 18/2 SJTOW Cord

**Cord Cap Options:** 5-15 Straight, 6-15 Straight, L5-15 Twist, L6-15 Twist, UKBS1363, Intl Schuko, Pigtail

**Housing Color:** Yellow

##### **Ratings/Approvals**

Impact Resistant

Dual Mounting Hooks

Padded End Caps

Inline Transformer

##### **Special Orders- Requirements**

Contact us for special requirements

**Toll Free:** 1-800-369-6671

**Intl:** 1-903-498-3363

**E-mail:** sales@larsonelectronics.com

**-Scroll Down to Purchase-**

Part #: [FTL-2-CFL-X12V-50 \(148210\)](#)

**Options:**FTL-2-CFL-X12V-50- **CORD CAP****Example:** FTL-2-CFL-X12V-50-5.15

CORD CAP	
5-15 Straight	-5.15
6-15 Straight	-6.15
L5-15 Twist	-L5.15
L6-15 Twist	-L6.15
UKBS1363	-BS1363
Intl Schuko	-Schuko
Pigtail	-Pigtail

Links (Click on the below items to view):

- [Manual](#)

- [Hi-Res Image 1- 13W CFL Drop Light w/ Inline Transformer](#)